

CASAMBI trailing edge phase control dimmer max. 100W

Order number: 5123

LED dimmer for convenient operation of lights via CASAMBI app using phase cut-off signal (max. 150W)

Controls the brightness of incandescent lamps, dimmable LED lamps and control gear for LEDs and halogen lamps (not for magnetic transformers)

Suitable for retrofitting phase cut-off dimmable lights (group control)

compatible with sensor (item no. 5117), radio remote control (item no. 5120) and wall switch (item no. 5121)

Complete control via CASAMBI app:

Configuration of luminaires and luminaire networks

Creation of scenes and animations (color gradients)

Intelligent timer and gallery functions

Power consumption in watts: max. 100; protection class (IP): IP20; Input voltage: 100 - 240 V AC; Input voltage span: 85-240 AC; Input voltage range luminaire: 85-240 AC; ETIM Gruppen-ID: EC002924; Compatible with Casambi: Yes; Compatible with Apple HomeKit: No; Compatible with Google Assistant: No; Compatible with Amazon Alexa: No; BEG funding: Only relevant in Germany
width: 37mm