

PRODUCT NO. 5277

**DOTLUX LED Wireless Receiver/DimmerTuya & Fusion Triac Receiver 1.5A 1Channel 100 - 240V AC**



to the product page



- WiFi Dotlux Fusion Technology Push AC phase angle dimmer, 1 channel output.
- For dimming and switching single color dimmable LED lamps or halogen lamps.
- Tuya APP cloud control, supports power on/off, brightness adjustment, delayed light on/off, timer, scene and music playback function.
- Voice control, supports Amazon ECHO and smart speakers.
- Dimming type adjustable by dip switch, phase cut/prime cut.
- minimum brightness can be preset via push button
- additional wired push button control input
- Each dimming module can also work as a TUYA to Fusion converter
- Via the Tuya APP, one or more LED controllers or drivers can be controlled synchronously
- Easy installation in standard wall junction boxes behind a push button
- Overheating/overload protection, automatic recovery
- Inrush current of connected LED luminaires/ballasts must not exceed 130A

<b>SUCCESSION ARTICLE</b>	-	<b>PROTECTION CLASS (IP)</b>	IP20
<b>WEIGHT IN KG</b>	0.048	<b>INPUT VOLTAGE SPAN</b>	100-240 AC
		<b>WARRANTY IN YEARS</b>	3
		<b>CONTROL METHOD</b>	Leading edge/trailing edge phase control
<b>Dimensions</b>		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	100-240 AC
<b>width:</b> 52mm		<b>ETIM GROUP IDENTIFICATION NUMBER</b>	EC002924
<b>height:</b> 26mm		<b>COMPATIBLE WITH CASAMBI</b>	No
<b>length:</b> 52mm		<b>COMPATIBLE WITH APPLE HOMEKIT</b>	Yes
		<b>COMPATIBLE WITH GOOGLE ASSISTANT</b>	Yes
		<b>COMPATIBLE WITH AMAZON ALEXA</b>	Yes
		<b>SUITABLE FOR DOTLUX FUSION</b>	Yes
		<b>SUITABLE FOR TUYA</b>	Yes
		<b>BEG FUNDING</b>	Only relevant in Germany