

PRODUCT NO. 3923-2

**DOTLUX EMERGENCY CURRENT AKKU-KITexit 1.9W/0.8W constant power 3/8h for constant current operated LED lights with ext. test button LifePO4 6.4V with self-test**



to the product page



- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- Emergency power operation also starts when the light is switched off and the mains power fails
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC
- The AKKU-KITexit emergency power supply is supplied with an operating status LED with installation socket and a test switch for external installation
- The AKKU-KITexit does not replace the power supply unit of the LED light. The AKKU-KITexit must be ordered in addition to the power supply unit.
- Automatic self-test
- The AKKU-KIT can be set to different levels: 0.8@8H / 1.9W@3H
- Consumption in charging mode 3Watt
- Consumption in standby mode less than 0.5Watt

<b>SUCCESSION ARTICLE</b>	-	<b>INPUT VOLTAGE</b>	220 - 240 V AC
<b>PREDECESSOR ARTICLE</b>	3923-1, 5806	<b>BATTERY RUNTIME</b>	8h at 0.8W
<b>WEIGHT IN KG</b>	0.27	<b>PROTECTION CLASS</b>	II
<b>POWER CONSUMPTION IN WATTS</b>	0,8 / 1,9	<b>SUITED FOR EMERGENCY LIGHTING</b>	yes
		<b>INPUT VOLTAGE SPAN</b>	220-240
		<b>WARRANTY IN YEARS</b>	3
		<b>CAPACITIY OF BATTERY IN MAH</b>	6000
		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	220-240
<b>Dimensions</b>		<b>SELF-TEST</b>	Automatic self-test
<b>height:</b> 25mm		<b>ETIM GRUPPEN-ID</b>	EC000471
<b>length:</b> 199mm		<b>SUITABLE FOR EMERGENCY LIGHTING</b>	Yes
<b>width:</b> 55mm		<b>BEG FUNDING</b>	Only relevant in Germany
		<b>LAMP TYPE</b>	Other