

PRODUCT NO. 5556

**DOTLUX EMERGENCY CURRENT ACCU KIT EMERGENCY LIGHT BATTERY 3.6W 50-200V Self-test constant power (3h) for constant current operated LED lights LiFePO4 6.4V**



to the product page



- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- If the light is switched off and the mains power fails, emergency power operation also starts
- The emergency power supply AKKU-KIT is ideal for retrofitting the DISCugr
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 50-200 V DC.
- The emergency power supply AKKU-KIT includes an operating status LED with installation socket and a test switch for external installation
- The AKKU-KIT does not replace the power supply unit of the LED light. The AKKU-KIT must be ordered in addition to the power supply unit.
- Automatic self-test function
- Consumption in charging mode 2.5 watts
- Consumption in standby mode less than 0.5Watt
- Temperature resistant from -20 to 55°C

<b>SUCCESSION ARTICLE</b>	-	<b>INPUT VOLTAGE</b>	220 - 240 V AC
<b>WEIGHT IN KG</b>	0.278	<b>BATTERY RUNTIME</b>	3h
<b>POWER CONSUMPTION IN WATTS</b>	3,6	<b>PROTECTION CLASS</b>	II
		<b>SUITED FOR EMERGENCY LIGHTING</b>	yes
		<b>INPUT VOLTAGE SPAN</b>	50-200
		<b>CAPACITIY OF BATTERY IN MAH</b>	3000
		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	50-200
<b>Dimensions</b>		<b>SELF-TEST</b>	Automatic self-test
<b>height:</b> 21mm		<b>ETIM GRUPPEN-ID</b>	EC000471
<b>length:</b> 158mm		<b>SUITABLE FOR EMERGENCY LIGHTING</b>	Yes
<b>width:</b> 30mm		<b>BEG FUNDING</b>	Only relevant in Germany
		<b>LAMP TYPE</b>	Other