

CASAMBI PWM dimmer 12-24V 4-channel max. 144W

Order number: 5115

- PWM dimmer with 4 channels for 12V or 24V for convenient operation of luminaires via CASAMBI App
- the dimmer is mounted between the non-dimmable 12-24 VDC control gear and the constant voltage product
- suitable for 1-color strips, COLORselect strips, RGB and RGBW strips
- the max. output current is 6A, this can be freely distributed to the channels 1-4
- protected against: overload, overcurrent and short circuit
- different pre-installed profiles are selectable in CASAMBI App
- compatible with sensor (art. no. 5117), radio remote control (art. no. 5120) and wall switch (art. no. 5121)
- Complete control via CASAMBI App:
- Control of brightness and light color
- Configuration of luminaires and luminaire networks
- creation of scenes and animations (color gradients)
- intelligent timer and gallery functions

Power consumption in watts: max. 144 bei 24V; protection class (IP): IP20; Output voltage: 12 - 24 DC; ETIM Group Identification Number: EC002924; Compatible with Casambi: Yes; Compatible with Apple HomeKit: No; Compatible with Google Assistant: No; Compatible with Amazon Alexa: No; BEG funding: Only relevant in Germany
width: 30mm