

DOTLUX EMERGENCY CURRENT ACCU KIT EMERGENCY LIGHT BATTERY 5W 10-90V Self-test constant power (3h) for constant current operated LED lights LiFePO4 7.3V

Order number: 4343-2

- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- If the light is switched off and the mains power fails, emergency power operation also starts
- The emergency power supply AKKU-KIT is primarily designed for retrofitting continuous-row lighting systems from the DOTLUX range, e.g. linear luminaires
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC.
- The emergency power supply AKKU-KIT includes an operating status LED with installation socket and a test switch for external installation
- The AKKU-KIT does not replace the power supply unit of the LED light. The AKKU-KIT must be ordered in addition to the power supply unit.
- Automatic self-test function
- Temperature resistant from -20 to 55°C

Power consumption in watts: 5; Input voltage: 220 - 240 V AC; Battery runtime: 3h; Protection class: II; Input voltage span: 10-90; Warranty in years: 3; Input voltage range luminaire: 10-90; ETIM Group Identification Number: EC000471; BEG funding: Only relevant in Germany; Lamp type: Other
width: 30mm