

DOTLUX EMERGENCY CURRENT AKKU-KITexit 1.9W/0.8W constant power 3/8h for constant current operated LED lights with ext. test button LifePO4 6.4V with self-test

Order number: 3923-2

- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- Emergency power operation also starts when the light is switched off and the mains power fails
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC
- The AKKU-KITexit emergency power supply is supplied with an operating status LED with installation socket and a test switch for external installation
- The AKKU-KITexit does not replace the power supply unit of the LED light. The AKKU-KITexit must be ordered in addition to the power supply unit.
- Automatic self-test
- The AKKU-KIT can be set to different levels: 0.8@8H / 1.9W@3H
- Consumption in charging mode 3Watt
- Consumption in standby mode less than 0.5Watt

Power consumption in watts: 0,8 / 1,9; Input voltage: 220 - 240 V AC; Battery runtime: 8h at 0.8W; Protection class: II; Suited for emergency lighting: yes; Input voltage span: 220-240; Warranty in years: 3; Capacity of battery in mAh: 6000; Input voltage range luminaire: 220-240; Self-test: Automatic self-test; ETIM Group Identification Number: EC000471; Suitable for emergency lighting: Yes; BEG funding: Only relevant in Germany; Lamp type: Other
width: 55mm