


PRODUCT NO. 5351

## CASAMBI PIR motion and brightness sensor for outdoor wall mounting



to the product page



- PIR motion and brightness sensor for convenient operation of luminaires via CASAMBI app
- Mounting height: max. 17m (ceiling mounting) for wall mounting recommended height 1 to 2.2m
- Extra sensitive motion sensor with extended detection range: 10-20m see graphics
- Power supply via 220V mains
- Complete control via CASAMBI App:
  - presence/absence detection
  - ambient light dependent control of luminaires/scenes
  - Light duration and fade-in/fade-out times

Assign the desired scenes to the sensor via app

- Automatically switch luminaires/devices on and off after motion detection
- Integrated brightness sensor - light intensity as required
- Absence setting - change dimming level in case of absence
- Day and night setting - individual light at specific times when motion is detected
- The motion detector can also be activated/deactivated by switch or timer

<b>SUCCESSION ARTICLE</b>	-	<b>INPUT VOLTAGE</b>	220 - 240 V AC
<b>WEIGHT IN KG</b>	0.107	<b>INRUSH CURRENT IN A</b>	0
		<b>WARRANTY IN YEARS</b>	2
		<b>HOUSING MATERIAL</b>	Polycarbonate
		<b>RADIO FREQUENCY</b>	2,4
		<b>MOUNTING LOCATION</b>	Indoor + Outdoor
		<b>ETIM GRUPPEN-ID</b>	EC002556
		<b>PULSE DURATION IN µS</b>	0
		<b>BEG FUNDING</b>	Only relevant in Germany
		<b>DREH- /SCHWENKBAR</b>	not swivelling
		<b>ADJUSTABILITY</b>	Not adjustable
		<b>COLOUR</b>	White

### Dimensions

**height:** 37mm  
**length:** 75mm  
**width:** 60mm