

PRODUCT NO. 5425-1

DOTLUX DALI trailing edge phase dimmer max. 200W



to the product page

- Dimmer with DALI control input for dimming 230V LED ballasts or LED lamps via DALI.
- With this LED trailing edge phase cut-off dimmer, you can easily integrate and control your dimmable luminaires in a DALI system.
- The LED dimmer converts the DALI dimming level into a dimmed 230V signal (trailing edge phase control).
- The dimmer is suitable for resistive and capacitive loads and is compatible with all trailing edge dimmable luminaires/power supply units.
- It is installed in a box.
- The minimum dimming level (MIN LEVEL) is adjustable.
- The LED leading edge phase control dimmer represents a device on the bus and can be addressed accordingly.
- dimmable LED lamps max 200Watt (max.130A inrush current)
- traditional light bulbs and halogen lamps max. 360W
- Integrated overheating protection with automatic recovery

SUCCESSION ARTICLE	-
PREDECESSOR ARTICLE	5425
WEIGHT IN KG	0.05
POWER CONSUMPTION IN WATTS	-
NET LUMINOUS FLUX IN LUMENS	-
LUMEN PER WATT	-

PROTECTION CLASS (IP)	IP20
INPUT VOLTAGE	100 - 240 V AC
LUMEN PER WATT	-
PROTECTION CLASS	none
OUTPUT VOLTAGE	100-240
INPUT VOLTAGE SPAN	100-240
WARRANTY IN YEARS	5
DIMMING WITHOUT DIMMER	No
INPUT VOLTAGE RANGE LUMINAIRE	100-240
MOUNTING LOCATION	Indoor
ETIM GRUPPEN-ID	EC002924
COMPATIBLE WITH CASAMBI	No
COMPATIBLE WITH APPLE HOMEKIT	No
COMPATIBLE WITH GOOGLE ASSISTANT	No
COMPATIBLE WITH AMAZON ALEXA	No
IFTTT SUPPORT AVAILABLE	No
SURFACE-MOUNTED	Yes
MODEL	statisch
DIN-RAIL MOUNTING	Yes
BUILT-IN	Yes
SUITABLE FOR OUTDOOR USE	No
HOUSING	Plastic housing
PROGRAMMABLE	No
SUITABLE FOR CASAMBI	No
SUITABLE FOR DOTLUX FUSION	No
SUITABLE FOR KEY OPERATION	Yes

Dimensions

length: 56mm
width: 50mm
height: 28mm

SUITABLE FOR TUYA
BEG FUNDING
CONTROL METHOD

No
Only relevant in Germany
Dali