

PRODUCT NO. 4335

## Changeover switch with monitoring module for Gessler system



to the product page



- Using the Gessler LB1/009 module, emergency and safety luminaires can be realized in one circuit (mixed technology) can be realized
- considerable savings during installation or reduction of the fire load
- The module is suitable for both AC and DC networks suitable
- The connected luminaires are monitored and switched via the switching input with the general lighting via the switching input
- Data transmission takes place on the supply line
- In the event of a fault the exact location can be shown on the display of the LPS/CPS system. displayed
- Only compatible with Gessler system
- Addresses 1-20
- Inrush current max- 45A/ 5ms
- Supply voltage 230V AC / 220 V DC
- Power range 2-200 W

<b>SUCCESSION ARTICLE</b>	-	<b>PROTECTION CLASS (IP)</b>	IP20
<b>WEIGHT IN KG</b>	0.033	<b>INPUT VOLTAGE</b>	220 - 240 V AC
<b>POWER CONSUMPTION IN WATTS</b>	2-200	<b>INRUSH CURRENT IN A</b>	0
		<b>PROTECTION CLASS</b>	I
		<b>INPUT VOLTAGE SPAN</b>	176-276 AC/DC
		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	176-276 AC/DC
		<b>ETIM GRUPPEN-ID</b>	ECC002710
<b>Dimensions</b>		<b>NO DIM FUNCTION</b>	Yes
<b>length:</b> 78mm		<b>COMPATIBLE WITH CASAMBI</b>	No
<b>width:</b> 30mm		<b>COMPATIBLE WITH APPLE HOMEKIT</b>	No
<b>height:</b> 20mm		<b>COMPATIBLE WITH GOOGLE ASSISTANT</b>	No
		<b>COMPATIBLE WITH AMAZON ALEXA</b>	No
		<b>PULSE DURATION IN µS</b>	0
		<b>BEG FUNDING</b>	Only relevant in Germany