

PRODUCT NO. 5350

CASAMBI switching relay / switching actuator for switching 220V consumers



to the product page

This CASAMBI relay allows lights and other consumers to be switched on and off via smartphone

- Complete control via CASAMBI App:
- Selectable operating modes/profiles
- Wireless control via app, wall switch and motion detector
- Automatic switching on and off according to times, days of the week, date or sun times
- Integration in scenes and animations

Simply select the appropriate profile via the app:

- Switch Actuator (switch actuator for lights)
- Push Actuator (push actuator: remains switched on as long as it is pushed)

LED lamps and transformers max.6A (1500W)

Incandescent/halogen lamps 10A (2300W)

Fans 1A (230W)

Inrush current max :120A, 20ms

SUCCESSION ARTICLE	-	PROTECTION CLASS (IP)	IP40
WEIGHT IN KG	0.109	INPUT VOLTAGE	100 - 240 V AC
POWER CONSUMPTION IN WATTS	<0,5	OUTPUT CURRENT IN A	10
		INRUSH CURRENT IN A	0
		PROTECTION CLASS	II
		OUTPUT VOLTAGE	potential-free
		WARRANTY IN YEARS	2
		MOUNTING LOCATION	Indoor
		ETIM GROUP IDENTIFICATION NUMBER	ECC002710
Dimensions		DIMMING 1-10 V	No
length: 120mm		DIMMING DALI	No
width: 50mm		DIMMING DMX	No
height: 33mm		DIMMING DSI	No
		DIMMING POTENTIOMETER (INTEGRATED)	No
		DIMMING LINESWITCH	No
		DIMMING MANUFACTURER'S PROPRIETARY SYSTEM	No
		DIMMING MAINS VOLTAGE MODULATION	No
		DIMMING PHASE CUT-OFF	No
		DIMMING PROGRAMMABLE	No
		DIMMING WITH PUSH-BUTTON	No
		NO DIM FUNCTION	Yes
		COMPATIBLE WITH CASAMBI	Yes
		COMPATIBLE WITH APPLE HOMEKIT	No

COMPATIBLE WITH GOOGLE ASSISTANT	No
COMPATIBLE WITH AMAZON ALEXA	No
SUITABLE FOR OUTDOOR USE	No
HOUSING	Plastic housing
DIMMING PHASE CUT-ON	No
PULSE DURATION IN μS	0
BEG FUNDING	Only relevant in Germany