

PRODUCT NO. 5806

**DOTLUX EMERGENCY CURRENT AKKU-KITexit 1.8W constant power 3h for constant current operated LED lights with ext. test button LiFePO4 6.4V with self-test**



to the product page



- In the event of a power failure, the kit provides emergency lighting for constant current-operated LED lights, which are then powered by the internal battery
- Emergency power operation also starts when the light is switched off and the mains power fails
- Can be used universally for all LED luminaires with external ballasts with an operating voltage of 10-90 V DC
- The AKKU-KITexit emergency power supply is supplied with an operating status LED with installation socket and a test switch for external installation
- The AKKU-KITexit does not replace the power supply unit of the LED light. The AKKU-KITexit must be ordered in addition to the power supply unit.
- Automatic self-test
- The AKKU-KIT can be set to different levels: 1.8W@3H / 2.9W@2H / 3.5W@1.5H
- Consumption in charging mode 2.5Watt
- Consumption in standby mode less than 0.5Watt

<b>SUCCESSION ARTICLE</b>	-	<b>INPUT VOLTAGE</b>	220 - 240 V AC
<b>WEIGHT IN KG</b>	0.27	<b>INRUSH CURRENT IN A</b>	0
<b>POWER CONSUMPTION IN WATTS</b>	1,8 / 2,9 / 3,5	<b>BATTERY RUNTIME</b>	3h
		<b>TC TEMPERATURE IN °C</b>	60
		<b>PROTECTION CLASS</b>	II
		<b>BATTERY-TYPE</b>	-
		<b>WARRANTY IN YEARS</b>	3
		<b>SELF-TEST</b>	Automatic self-test
		<b>ETIM GROUP IDENTIFICATION NUMBER</b>	EC000471
		<b>PULSE DURATION IN µS</b>	0
		<b>BEG FUNDING</b>	Only relevant in Germany
		<b>LAMP TYPE</b>	Other
<b>Dimensions</b>			
<b>length:</b>	199mm		
<b>width:</b>	55mm		
<b>height:</b>	25mm		