

**DOTLUX Remote control for MISTRALsmart**

Order number: 5437

Remote control for DOTLUX damp-proof luminaire MISTRALsmart

- This remote control is needed to adjust the sensor of the MISTRALsmart luminaires.
  - You need only one remote control for any number of luminaires
  - The infrared remote control must be pointed at the luminaire to change settings
  - The luminaire visually acknowledges the setting by flashing
- The following values can be set:
  - Power (80%, 100%)
  - brightness (20% - 100%)
  - detection range (25%, 50%, 75%, 100%)
  - Light duration (3sec, 30sec, 90sec, 3min, 5min, 15min, 20min, 30min)
  - Stand-by brightness (10%, 20%, 30%, 50%)
  - Stand-by duration (0sec, 5sec, 30sec, 3min, 5min, 15min, 45min, permanent)
  - Daylight sensor (5lux, 15lux, 50lux, 100lux, 300lux, disable)

Warranty in years: 3; ETIM Group Identification Number: EC000678; Wireless: Yes; Bi-directional: No; Uni-directional: Yes; Adaptive (self-learning): Yes; With display: No; Pre-programmed: Yes; BEG funding: Only relevant in Germany; Signal transmission: Other  
width: 55mm