

PRODUCT NO. 5076

LED power supply CV 24V DC 0-60W 0-2,5A not dimmable IP20 linear



to the product page

The power supply is not dimmable

With constant voltage (CV) technology, it is suitable for constant voltage luminaires

<b>SUCCESSION ARTICLE</b>	-	<b>PROTECTION CLASS (IP)</b>	IP20
<b>WEIGHT IN KG</b>	0.211	<b>INPUT VOLTAGE</b>	176 - 240 V AC/DC
<b>POWER CONSUMPTION IN WATTS</b>	0-60	<b>OUTPUT CURRENT IN A</b>	0-2,5
		<b>TC TEMPERATURE IN °C</b>	80
		<b>PROTECTION CLASS</b>	I
		<b>SUITED FOR EMERGENCY LIGHTING</b>	yes
		<b>OVERVOLTAGE PROTECTION</b>	2000 V
		<b>OUTPUT VOLTAGE</b>	24 DC
		<b>INPUT VOLTAGE SPAN</b>	176-264 AC / 170-275 DC
		<b>WARRANTY IN YEARS</b>	3
		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	176-264 AC / 170-275 DC
		<b>ETIM GRUPPEN-ID</b>	EC002710
		<b>DIMMING 0-10 V</b>	No
		<b>DIMMING 1-10 V</b>	No
		<b>DIMMING DALI</b>	No
		<b>DIMMING DMX</b>	No
		<b>DIMMING DSI</b>	No
		<b>DIMMING POTENTIOMETER (INTEGRATED)</b>	No
		<b>DIMMING LINESWITCH</b>	No
		<b>DIMMING MANUFACTURER'S PROPRIETARY SYSTEM</b>	No
		<b>DIMMING MAINS VOLTAGE MODULATION</b>	No
		<b>DIMMING PHASE CUT-OFF</b>	No
		<b>DIMMING PROGRAMMABLE</b>	No
		<b>DIMMING RF</b>	No
<b>Dimensions</b>			
<b>length:</b>	250mm		
<b>width:</b>	30mm		
<b>height:</b>	21mm		

<b>DIMMING SINE WAVE REDUCTION</b>	No
<b>DIMMING TOUCH AND DIM</b>	No
<b>DIMMING ZIGBEE</b>	No
<b>DIMMING WITH PUSH-BUTTON</b>	No
<b>NO DIM FUNCTION</b>	Yes
<b>SUITABLE FOR EMERGENCY LIGHTING</b>	Yes
<b>COMPATIBLE WITH CASAMBI</b>	No
<b>COMPATIBLE WITH APPLE HOMEKIT</b>	No
<b>COMPATIBLE WITH GOOGLE ASSISTANT</b>	No
<b>COMPATIBLE WITH AMAZON ALEXA</b>	No
<b>DIMMING PHASE CUT-ON</b>	No
<b>DIMMING GPRS</b>	No
<b>BEG FUNDING</b>	Only relevant in Germany