

PRODUCT NO. 5180

DOTLUX LED rotary dimmer 5-100W dimmable phase section



to the product page



- The LED rotary dimmer is compatible with phase cut-off dimmable LED luminaires.
- With constant current (CC) technology, it is suitable for constant current luminaires
- The connected constant current luminaires can be dimmed between 1%-100%
- Suitable for the following systems:
 - Berker by Hager
 - Busch-Jaeger
 - GIRA
 - JUNG
 - Merten by Schneider
 - NIKO
 - PEHA
 - Exxact
 - ELKO R5

SUCCESSION ARTICLE	-	PROTECTION CLASS (IP)	IP20
WEIGHT IN KG	0.064	INPUT VOLTAGE	220 - 240 V AC
POWER CONSUMPTION IN WATTS	5 - 100	PROTECTION CLASS	none
		OUTPUT VOLTAGE	200
		CONTROL METHOD	Sine Wave Reduction
		DIMMING WITHOUT DIMMER	No
		ETIM GRUPPEN-ID	EC002924
Dimensions		COMPATIBLE WITH CASAMBI	No
height: 25mm		COMPATIBLE WITH APPLE HOMEKIT	No
diameter: 71mm		COMPATIBLE WITH GOOGLE ASSISTANT	No
length: 71mm		COMPATIBLE WITH AMAZON ALEXA	No
width: 71mm		SURFACE-MOUNTED	No
		MODEL	Dynamic
		DIN-RAIL MOUNTING	No
		BUILT-IN	Yes
		SUITABLE FOR OUTDOOR USE	No
		HOUSING	Plastic housing
		PROGRAMMABLE	No
		SUITABLE FOR CASAMBI	No
		SUITABLE FOR DOTLUX FUSION	No
		SUITABLE FOR KEY OPERATION	No
		SUITABLE FOR TUYA	No
		BEG FUNDING	Only relevant in Germany