

PRODUCT NO. 5278

**DOTLUX LED Wireless Receiver/Dimmer Fusion Technology Triac Receiver 2.0A 1 Channel 100 - 240V AC**



to the product page



- Dotlux Fusion Technology Push AC phase angle dimmer, 1 channel output.
- - For dimming and switching of single color dimmable LED lamps or halogen lamps.
- - Dimming mode adjustable via dip switch, phase cut/angle cut
- - minimum brightness can be preset by push button
- - additional wired 1-10V push button control input
- - overheat/overload protection, automatic recovery
- - inrush current of connected LED luminaires/ballasts must not exceed 130A

<b>SUCCESSION ARTICLE</b>	-	<b>PROTECTION CLASS (IP)</b>	IP20
<b>WEIGHT IN KG</b>	0.121	<b>INPUT VOLTAGE SPAN</b>	100-240 AC
		<b>WARRANTY IN YEARS</b>	3
		<b>INPUT VOLTAGE RANGE LUMINAIRE</b>	100-240 AC
		<b>ETIM GRUPPEN-ID</b>	EC002924
<b>Dimensions</b>		<b>COMPATIBLE WITH CASAMBI</b>	No
		<b>COMPATIBLE WITH APPLE HOMEKIT</b>	No
		<b>COMPATIBLE WITH GOOGLE ASSISTANT</b>	Yes
<b>height:</b> 27mm		<b>COMPATIBLE WITH AMAZON ALEXA</b>	No
<b>length:</b> 175mm		<b>BEG FUNDING</b>	Only relevant in Germany
<b>width:</b> 45mm			